

Technical Data Sheet Voice Coil Bonder 360

April 2019

Page 1 of 2

Product Description

Hernon[®] Voice Coil Bonder 360 is a single component, black, heat cure adhesive formulated for bonding and coating voice coil components and high temperature lamination. The cured bond withstands temperatures exceeding 600°F (316°C).

Product Benefits

- Single component
- Excellent resistance to high temperature, chemicals, and water
- Flexible, thermal shock resistant bond
- Excellent adhesion
- High strength at room temperature and elevated temperatures.

Typical Applications

- Coating of Aluminum, copper-clad and copper wire coils.
- Coating of form materials including Kapton[®] H, HN, HPPST AND MTB, fiberglass composite, aluminum and Nomex[®].

Typical Properties (Uncured)

Property	Value
Base	Nitrile Phenolic
Solvent	Methyl ethyl ketone
Appearance	Black liquid
Viscosity @ 25°C, cP	4,000 to 6000 ¹
Specific gravity	0.94
Solid Content %	31- 39

¹ Viscosity may increase over time. It may be necessary to add a small amount of solvent to adjust the viscosity of aged material.

Typical Properties (Cured)

Disc Shear strength, tested according to SAE J840

Temperature	Shear Strength, lb
73°F (22°C)	2500 - 4500
400°F (204°C)	500 - 1500

General Information

For safe handling information on this product, consult the Safety Data Sheet (SDS).

Directions for use

Application

1. Clean bonding surfaces.
2. Coat with adhesive on surfaces. The dry film thickness should be 0.008 to 0.015 in. (0.20 to 0.38 mm), 0.025 to 0.045 in. wet (0.635 to 1.14 mm) depending on the coverage pattern used.

Note: Humidity affects solvent evaporation rates. This can cause a drying problem during summer months. Normal drying cycles may require seasonal adjustments to provide adequate drying.

3. Former: Apply **Voice Coil Bonder 360** to the former surfaces to be bonded. Allow the adhesive to become "tack free" at room temperature for approximately 10 minutes (Warm air circulation will speed up the "tack free time"). Place the parts in an oven for 30 minutes at 82.0°C. Afterwards, parts can be stored in a dry environment for future winding.
4. Wire: The wire manufacturer specifies the thickness of the insulation coating. As a general rule, the thickness of **Voice Coil Bonder 360** should be the same as the thickness of the wire insulation. Thinner wires would have a thinner insulation therefore the **Voice Coil Bonder 360** coating would also be less. After applying the adhesive, run the wire for ± 30 seconds through the oven at 82.0°C until it becomes tack free. Assure that the wire is not kept in the oven too long, otherwise cross-linking will occur. Test: If acetone or MEK is applied on the wire, it should get tacky again. If this does not happen, the exposure in the oven was too long and cross-linking already occurred. Afterwards the wire can be stored for future winding.
5. Reactivate **Voice Coil Bonder 360** on the wire and the former by passing it through a sponge saturated with acetone or MEK. The adhesive will get "tacky" again.
6. Wind the tacky coated wire on the former and place in the oven for 20 minutes at 82.0°C, followed by 204°C for 45 minutes to achieve cross-linking. Afterwards, allow relaxation and outgassing of the completed bobbin by final oven cure at 65°C for 12 hours. This procedure will prevent blistering when high temperature is applied.

7. Heavier Gauge Wire increases the cross-linking in the oven.
8. Dilution: Voice Coil Bonder can be diluted as necessary to achieve the desired viscosity the percentage of dilution is as follows:
 - MEK – unlimited
 - Acetone – unlimited
 - Alcohol – Less than 25%

Kapton® and Nomex® are trademarks of E.I. DuPont de Nemours & Co., Inc.

Curing

1. **Voice Coil Bonder 360** can be cured using an oven. Oven-type heating unit, whether infrared, gas or electric, should maintain even temperature and have adequate air circulation. Pressure jigs are used to force the gas and vapors out of the adhesive during bonding. If there is not enough pressure or full contact the bond will be weak and spongy.
2. A minimum cure cycle of 30 minutes at 400°F is recommended.
3. For fixturing purposes solvent reactivation may be possible by using acetone, MEK or butyl acetate. For some applications, this adhesive may be applied to one part only.

Clean up

Prior to cure, the adhesive can be removed with MEK. Work should be done in a well-ventilated area.

Following cure, the adhesive will be resistant to basically all solvents. The only practical means of cleaning a cured adhesive is with some type of abrasion.

Storage

Voice Coil Bonder 360 should be stored in a cool, dry location in unopened containers at a temperature between 40°F to 60°F (4°C to 16°C) unless otherwise labeled. Optimal storage is at the lower half of this temperature range. To prevent contamination of unused material, do not return any material to its original container.

Dispensing Equipment

Hernon® offers a complete line of semi and fully automated dispensing equipment. Contact **Hernon® Sales** for additional information.

These suggestions and data are based on information we believe to be reliable and accurate, but no guarantee of their accuracy is made. HERNON MANUFACTURING, INC. shall not be liable for any damage, loss or injury, direct or consequential arising out of the use or the inability to use the product. In every case, we urge and recommend that purchasers, before using any product in full scale production, make their own tests to determine whether the product is of satisfactory quality and suitability for their operations, and the user assumes all risk and liability whatsoever, in connection therewith. Hernon's Quality Management System for the design and manufacture of high-performance adhesives and sealants is registered to the ISO 9001 Quality Standard.